

VOLTAGE PHASING METERS

- 2 Models to choose from - Digital and Analog
- Instrument for measuring overhead and underground voltages.
- Two modes of operation AC and Hi-Pot.
- 0-40KV meter up to 240KV with resistors.
- Automatically adjust voltage display to match resistors if used.
- Hi-Pot mode for testing URD Cable.
- In Hi-Pot mode bar graph marks the peak voltage while cable is being charged.
- Large easy to read digital meter and analog bar graph.
- Digital meter reads to nearest 100 volts.
- Meter has lighted background that can be turned on for use in poor light conditions.
- Meter enclosure made of high quality rugged extruded aluminum.
- Auto shutdown after 40 minutes if no voltage is detected.
- Long battery life from three AA's.
- Auto self test and battery check during start up.
- The coiled, self retracting cable is 16" retracted and 10' when fully extended.
- Units: Include volt meter, conductor hooks, carry case, batteries, and instructions.

CAT NO	DESCRIPTION	LBS
6702	DIGITAL VOLT METER 0-40KV	5.0
6702-A	ANALOG VOLT METER 0-40KV	5.0
6703	PAIR OF EXTENSION RESISTORS FOR USE WITH MODEL 6702	1.3
6702-1	ONE 15/25KV LOADBREAK BUSHING ADAPTER	0.6
6702-3	ONE 35KV LOADBREAK BUSHING ADAPTER	0.5
6702-2	ONE D.C. HIPOT ADAPTER FOR USE UP TO 35KV	0.5
A30395	REPLACEMENT CARRYING CASE	2.1
6711	KIT INCLUDES 6702 WITH CASE, (2) 6' UNIVERSAL FIBERGLASS POLES WITH CARRYING CASE	10.0
6711-A	KIT INCLUDES 6702-A WITH CASE, (2) 6' UNIVERSAL FIBERGLASS POLES WITH CARRYING CASE	10.0

DIGITAL METER

ANALOG METER



6702



TOP DISPLAY OF VOLT METERS



6702-A



6702-1



6702-2



6702-3



6703